

# Star Wars

Near the planet Mars, in a faraway galaxy eerily similar to our own, there is a fight to the death between the imperial forces and the rebels. The rebel army has  $N$  ships which we will consider as points  $(x_i, y_i, z_i)$ . Each ship has a receiver with power  $p_i$ . The rebel army needs to be able to send messages from the central cruiser to all the ships, but they are tight on finances, so they cannot afford a strong transmitter.

If the cruiser is placed at  $(x, y, z)$ , and one of the other ships is at  $(x_i, y_i, z_i)$  and has a receiver of power  $p_i$ , then the power of the cruiser's transmitter needs to be at least:

$$(|x_i - x| + |y_i - y| + |z_i - z|) / p_i$$

Your task is to find the position for the cruiser that minimizes the power required for its transmitter, and to output that power.

## Input

The first line of input gives the number of cases,  $T$ .  $T$  test cases follow.

Each test case contains on the first line the integer  $N$ , the number of ships in the test case.

$N$  lines follow, each line containing four integer numbers  $x_i, y_i, z_i$  and  $p_i$ , separated by single spaces. These are the coordinates of the  $i$ -th ship, and the power of its receiver. There may be more than one ship at the same coordinates.

$$1 \leq T \leq 20$$

$$0 \leq x_i, y_i, z_i \leq 10^6$$

$$1 \leq p_i \leq 10^6$$

$$1 \leq N \leq 1000$$

## Output

For each input case, you should output:

Case # $X$ :  $Y$

where  $X$  is the number of the test case and  $Y$  is the minimal power that is enough to reach all the fleet's ships. Answers with a relative or absolute error of at most  $10^{-6}$  will be considered correct.

## Example

**Input:**

```
3
4
0 0 0 1
1 2 0 1
3 4 0 1
2 1 0 1
```

1  
1 1 1 1  
3  
1 0 0 1  
2 1 1 4  
3 2 3 2

**Output:**

Case #1: 3.500000

Case #2: 0.000000

Case #3: 2.333333